





SINKA DC-Line SMD Comon Mode Choke Coil OC & MCT series

Series Name	Dimention		Application	Usage	Parts No.	Rated Voltage (V, DC)	Rated Curent (A)	Impedance (Ω) at 100MHz min	Rdc (m Ω /Line)	Remark
MCT7050	5.2 x 7.2 x 2.7max		FA-machine	CC-Link Signal Line	MCT7050-A401	50	0.5	400 (50~300MHz)	300	TDK ZCYS51R5-M3PAT-01 Equivalent High Frequency
OC9070	7.0 x 10.5 x 4.7max		Game-machine Audio	Power Line	OC9070-C701	50	5.0	500	25	TDK ACM9070-701-2PL Equivalent High Frequency
OC9080	9.5 x 8.3 x 5.3max		MFP Telephone Adopter	Power Line	OC9080-A501	80	5.0	300	10	High Frequency
					OC9080-A801	80	3.5	600	20	
					OC9080-A102	80	2.5	800	50	
					OC9080-D601	80	5.0	350	10	
					OC9080-D102	80	3.5	600	20	
					OC9080-D152	80	2.5	1000	50	
			Telephone Senser	Signal Line	OC9080-M102	80	1.9	800	36	High Frequency
					OC9080-M122	80	0.8	900	85	
					OC9080-M152	80	0.5	1100	300	
					OC9080-S022	50	0.5	800 (at 100kHz)	500	
OC5750	6.2 x 5.5 x 3.5max		MFP Camera-Module Scanner Telephone	Power Line	OC5750-A301	80	2.5	200	25	High Frequency
					OC5750-A601	80	1.9	450	40	
					OC5750-A701	80	1.6	500	50	
					OC5750-A801	80	1.4	600	100	
					OC5750-A102	80	1.0	800	150	
					OC5750-D251	80	2.5	150	25	
					OC5750-D102	80	1.4	500	100	
					OC5750-D152	80	1.0	700	150	